


## A-O MODULATOR DRIVER

The Model ME series Modulator Drivers include a crystal controlled RF oscillator, fast modulation circuit, and a broadband RF power amplifier in a housing with power supply, RFI line filter, and line switch. The standard crystal controlled oscillator has a calibration tolerance of 25 ppm. Crystals at other than the specified frequencies can be factory installed. The standard modulation input configuration is analog with a digital input option available. A cw RF output level is adjusted by the front panel level control which inserts a dc offset to the input of the modulation circuit with no modulation input voltage. The class AB broadband amplifier has sufficient bandwidth for pulsed operation. RF output power capability can be up to 10 watts for some models. Configuration options include a front panel user accessible connection between the oscillator and modulation circuit (N) so that an external source frequency can be used in place of the internal crystal oscillator. Also available is an optional front panel connection between the modulation circuit and the RF power amplifier (H) to give the Model ME drivers capability to be used as a stand alone RF power amplifier. Drivers with option E provide a cw +10 dBm crystal oscillator reference output.

SPECIFICATION		
Input Configuration	Analog (1 volt peak-to-peak)	
RF Amplifier Operation	Class AB	
Rise/Fall Time	30 nsec	
Harmonics (at full power)	-20 dBc	
Output Mismatch Tolerance	100 percent	
Input / Output Impedance	50 ohms	
Line Voltage (standard)	115/230 Vac, 50-60 Hz	
	100 Vac, 50-60 Hz (option J)	
Size	9.0 W x 3.5 H x 13.5 D inches	
	22.9 W x 8.9 H x 34.3 D cm	

Model	ME-40	ME-405	ME-4010	ME-80	ME-110	ME-2001
Oscillator Frequency <sup>1</sup>	40 MHz	40 MHz	80 MHz	80 MHz	110 MHz	200 MHz
RF Output Power <sup>2</sup>	2W	5W	10W	2W	2W	1W

OPTIONS: D... Inverse digital, input<0.8 volts for RF/on, input>2 volts to 5 volts for RF off, 50 Ω impedance.

E...Low level oscillator RF output, +10 dBm level.

H... Front panel access between modulator circuit and RF power amplifier.

J... 100 Vac line voltage for Japan.

N... Front panel access between oscillator and modulator circuit.

P... Internal pulse generator for q-switch applications with triggered, gated, and free running capability.

T...Digital input, input<0.8 volts for RF/off, input>2 volts to 5 volts for RF/on, 50 Ω impedance.

T7... Same as option T, but with 70 dB extinction ratio.

-6... Analog input plus option T (analog + digital), total extinction ratio is 70 dB.

<sup>1</sup> Other frequencies are available. <sup>2</sup>Other RF output power levels are available.

